



SAW Components

Data Sheet B3894





SAW Components

B3894

Low Loss Filter for Mobile Communication

210,00 MHz

Data Sheet




Features

- IF filter for mobile telephone
- Channel selection in CDMA systems
- Low insertion attenuation
- Extremely high rejection
- Single-ended/single-ended, balanced/single-ended and balanced/balanced operation possible
- Optimized for single-ended/balanced operation
- Very small size
- Package for **Surface Mounted Technology (SMT)**

Terminals

- Ni, gold plated


Ceramic package **QCC8C**



Dimensions in mm, approx. weight 0,07 g

Pin configuration

- 2 Input
- 1+3 Input ground or balanced input
- 6 Output
- 5 Output ground or balanced output
- 7 to be grounded
- 4, 8 Case ground



Device is reciprocal, i.e. inputs can be used as outputs and vice versa

Type	Ordering code	Marking and Package according to	Packing according to
B3894	B39211-B3894-U310	C61157-A7-A56	F61074-V8169-Z000

Electrostatic Sensitive Device (**ESD**)

Maximum ratings

Operable temperature range	T	- 30/+ 85	°C
Storage temperature range	T_{stg}	- 40/+ 85	°C
DC voltage	V_{DC}	0	V
Source power	P_s	10	dBm



SAW Components

B3894

Low Loss Filter for Mobile Communication

210,00 MHz

Data Sheet



Characteristics single-ended/balanced


Operating temperature: $T = -30\text{ °C} \dots +80\text{ °C}$
 Terminating source impedance: $Z_S = 1000\ \Omega \parallel 70\text{ nH}$
 Terminating load impedance: $Z_L = 400\ \Omega \parallel 60\text{ nH}$

		min.	typ.	max.	
Nominal frequency	f_N	—	210,00	—	MHz
Insertion attenuation at f_N (including loss in matching network without loss in baluns)	α_{fN}	—	8,5	10,0	dB
Amplitude ripple (p-p) $f_N - 0,30 \dots f_N + 0,30$ MHz	$\Delta\alpha$	—	0,6	1,2	dB
Phase linearity (rms deviation) $f_N - 0,63 \dots f_N + 0,63$ MHz	$\Delta\phi$	—	2,5	3,5	°
Relative attenuation (relative to α_{fN}) $f_N - 0,63 \dots f_N + 0,63$ MHz	α_{rel}	—	3,5	5,0	dB
$f_N - 100,0 \dots f_N - 50,0$ MHz		60,0	80,0	—	dB
$f_N - 50,0 \dots f_N - 30,0$ MHz		50,0	65,0	—	dB
$f_N - 30,0 \dots f_N - 10,0$ MHz		40,0	55,0	—	dB
$f_N - 10,0 \dots f_N - 1,25$ MHz		35,0	38,0	—	dB
$f_N - 1,25$ MHz		37,0	41,0	—	dB
$f_N + 1,25$ MHz		37,0	41,0	—	dB
$f_N + 1,25 \dots f_N + 10,0$ MHz		35,0	41,0	—	dB
$f_N + 10,0 \dots f_N + 30,0$ MHz		40,0	55,0	—	dB
$f_N + 30,0 \dots f_N + 50,0$ MHz		50,0	60,0	—	dB
$f_N + 50,0 \dots f_N + 100,0$ MHz		60,0	70,0	—	dB
Temperature coefficient of frequency ¹⁾	TC_f	—	-0,036	—	ppm/K ²
Frequency inversion point	T_0	—	30	—	°C


¹⁾ Temperature dependence of f_c : $f_c(T) = f_c(T_0)(1 + TC_f(T - T_0)^2)$



Transfer function (passband, single-ended/balanced):




Transfer function (narrowband, single-ended/balanced):





Transfer function (wideband, single-ended/balanced):





SAW Components

B3894

Low Loss Filter for Mobile Communication

210,00 MHz

Data Sheet



Published by EPCOS AG

Surface Acoustic Wave Components Division, SAW MC IS

P.O. Box 80 17 09, 81617 Munich, GERMANY

© EPCOS AG 2004. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.